

LONG-RANGE DEPENDENT COMPLETELY CORRELATED MIXED FRACTIONAL BROWNIAN MOTION

Tommi Sottinen

University of Vaasa, Finland

This joint work with Josephine Dufitinema (U Vaasa), Foad Shokrollahi (U Vaasa), and Lauri Viitasaari (Aalto U)

Modern Stochastics: Theory and Applications. V
Kyiv, Ukraine, 4 Jun 2021

THE REFERENCE

JOSEPHINE DUFITINEMA, FOAD SHOKROLLAHI, TOMMI
SOTTINEN, LAURI VIITASAARI (2021)
Long-range dependent completely correlated mixed fractional
Brownian motion,
arXiv:2104.04992

ABSTRACT

We introduce the long-range dependent completely correlated mixed fractional Brownian motion (ccmfBm). This is a process that is driven by a mixture of Brownian motion (Bm) and a long-range dependent fractional Brownian motion (fBm) that is constructed from the Brownian motion via a Molchan–Golosov representation. Thus, there is a single Brownian motion driving the ccmfBm process.

We provide an inverse transfer principle for the ccmfBm and use it to construct Cameron–Martin–Girsanov–Hitsuda theorem and prediction formulas.

The talk is based on a joint work with Josephine Dufitinema (U Vaasa, Vaasa, Finland), Foad Shokrollahi (U Vaasa, Vaasa, Finland), and Lauri Viitasaari (Aalto U, Espoo, Finland).

OUTLINE

- 1 CONSTRUCTION OF CCMFBM
- 2 MOTIVATION
- 3 (INVERSE) TRANSFER PRINCIPLE
- 4 APPLICATIONS

OUTLINE

- 1 CONSTRUCTION OF CCMFBM
- 2 MOTIVATION
- 3 (INVERSE) TRANSFER PRINCIPLE
- 4 APPLICATIONS

CONSTRUCTION OF CCMFBM

Take a Brownian motion (Bm) $W = (W_t)_{t \in [0, T]}$. Construct a completely correlated fractional Brownian motion (ccfBm, fBm) with $H > 1/2$ from the Bm by using the Molchan–Golosov kernel

$$B_t^H = \int_0^t K_H(t, s) dW_s,$$
$$K_H(t, s) = c(H) \frac{1}{s^{H-\frac{1}{2}}} \int_s^t \frac{u^{H-\frac{1}{2}}}{(u-s)^{\frac{3}{2}-H}} du,$$

and then, from the **SAME** Bm construct the long-range dependent completely correlated mixed fractional Brownian motion (ccmfBm):

$$X_t = X_t^{a,b,H} = aW_t + bB_t^H.$$

OUTLINE

- 1 CONSTRUCTION OF CCMFBM
- 2 MOTIVATION
- 3 (INVERSE) TRANSFER PRINCIPLE
- 4 APPLICATIONS

MOTIVATION

The ccmfBm does not have stationary increments. A more natural mixed fractional Brownian motion (mfBm) would be

$$M_t = aW_t + bB_t^H,$$

where W and B^H are independent. This process has been studied in many articles.

However, ccmfBm is more convenient than mfBm because, as we will see, it has easier **INVERSE TRANSFER PRINCIPLE**. Also, the ccmfBm and the mfBm are similar in the sense that their short-time and long-time behaviors are mostly same (Hölder continuity, quadratic variation, long-range dependence).

OUTLINE

- 1 CONSTRUCTION OF CCMFBM
- 2 MOTIVATION
- 3 (INVERSE) TRANSFER PRINCIPLE
- 4 APPLICATIONS

(INVERSE) TRANSFER PRINCIPLE

Let $L^2 = L^2([0, T])$. For a kernel $K: [0, T]^2 \rightarrow \mathbb{R}$ its **ASSOCIATED OPERATOR** is

$$Kf(t) = \int_0^T f(s)K(t, s) du.$$

The **ADJOINT ASSOCIATED OPERATOR** K^* of a kernel K is defined by linearly extending the relation

$$K^*1_t(s) = K(t, s),$$

where $1_t = 1_{[0, t)}$ is the indicator function.

(INVERSE) TRANSFER PRINCIPLE

If $K(\cdot, t)$ has bounded variation, then (more or less)

$$\mathbb{K}^* f(t) = f(t)K(T, t) + \int_t^T [f(u) - f(t)] K(du, t).$$

Since the Molchen–Golosov kernel $K_H(t, s)$ for $H > 1/2$ is differentiable in t and $K_H(t, t-) = 0$, its adjoint associated operator can be written as

$$\mathbb{K}_H^* f(t) = \int_t^T f(u) \frac{\partial K_H}{\partial u}(u, t) du.$$

(INVERSE) TRANSFER PRINCIPLE

Let Λ be the closure of the indicator functions 1_t , $t \in [0, T]$, under the inner product generated by the relation

$$\langle 1_t, 1_s \rangle_\Lambda = R(t, s),$$

where R is the covariance of the ccmfBm.

Let \mathcal{H}_1 be the linear space, or first chaos, of X , i.e., the closure of the random variables X_t , $t \in [0, T]$, in $L^2(\Omega)$.

For $f \in \Lambda$ the abstract Wiener integral

$$\int_0^T f(t) dX_t$$

is the image of the isometry $1_t \mapsto X_t$ from Λ to \mathcal{H}_1 .

Denote $L(t, s) = a1_t(s) + bK_H(t, s)$ and let L and L^* be the associated and adjoint associated operators of L .

(INVERSE) TRANSFER PRINCIPLE

LEMMA (1)

L^* is a bounded operator on L^2 and it can be represented as

$$\begin{aligned} L^*f(t) &= af(t) + b \int_t^T f(u) \frac{\partial K_H}{\partial u}(u, t) du \\ &= af(t) + \frac{bc(H)}{t^{H-\frac{1}{2}}} \int_t^T f(u) \frac{u^{H-\frac{1}{2}}}{(u-t)^{\frac{3}{2}-H}} du. \end{aligned}$$

(INVERSE) TRANSFER PRINCIPLE

BEEF OF PROOF: K_H^* is bounded on L^2 , because

$$\begin{aligned}\|K_H^* f\|_2^2 &= \int_0^T \int_0^T f(t)f(s) \frac{\partial^2 R_H}{\partial s \partial t}(t, s) \, ds dt \\ &= H(2H - 1) \int_0^T \int_0^T \frac{f(t)f(s)}{|t - s|^{2-2H}} \, ds dt \\ &\leq H(2H - 1) \int_0^T \int_0^T \frac{f(t)^2}{|t - s|^{2-2H}} \, ds dt \\ &\leq H(2H - 1) \frac{T^{2H-1}}{H - \frac{1}{2}} \|f\|_2^2,\end{aligned}$$

where we have used the elementary estimate

$$2|f(t)f(s)| \leq f(t)^2 + f(s)^2$$

and symmetry.

(INVERSE) TRANSFER PRINCIPLE

LEMMA (2)

For each $t \in [0, T]$, the integral equation

$$1_t(s) = aL^{-1}(t, s) + b \int_s^T L^{-1}(t, u) \frac{\partial K_H}{\partial u}(u, s) du$$

admits the unique L^2 -solution given by

$$L^{-1}(t, s) = \frac{1}{a} 1_t(s) + \frac{1}{a} \sum_{k=1}^{\infty} (-1)^k \left(\frac{b}{a}\right)^k \gamma_k(t, s)$$

where

$$\gamma_k(t, s) = \frac{c(H)^k \Gamma(H - \frac{1}{2})^k}{\Gamma(k(H - \frac{1}{2}))} \frac{1}{s^{H-\frac{1}{2}}} \int_s^t u^{H-\frac{1}{2}} (u-s)^{k(H-\frac{1}{2})-1} du.$$

(INVERSE) TRANSFER PRINCIPLE

BEEF OF PROOF: Denote

$$G(s, u) = -\frac{bc(H)}{a} \frac{u^{H-\frac{1}{2}}}{s^{H-\frac{1}{2}}(u-s)^{\frac{3}{2}-H}}.$$

Then Lemma 2 has the anti-Volterra equation of the second kind

$$\frac{1}{a} \mathbf{1}_t(s) = L^{-1}(t, s) - \int_s^t L^{-1}(t, u) G(s, u) du.$$

Lemma 1 implies that the solution of the equation in Lemma 2 is

$$L^{-1}(t, s) = \sum_{k=1}^{\infty} G^k \left[\frac{1}{a} \mathbf{1}_t \right] (s),$$

where G^0 is the identity operator and $G^{k+1} = GG^k$. Finally, we use induction with the formula ($\alpha = H - \frac{1}{2}$)

$$\int_s^u (v-s)^{k\alpha-1} (u-v)^{\alpha-1} dv = \frac{\Gamma(k\alpha)\Gamma(\alpha)}{\Gamma((k+1)\alpha)} (u-s)^{(k+1)\alpha-1}.$$

(INVERSE) TRANSFER PRINCIPLE

THEOREM (1)

The ccmfBm X is an invertible Gaussian Volterra process in the sense that the process W defined as the abstract Wiener integral

$$W_t = \int_0^t L^{-1}(t, s) dX_s$$

is the Bm from which the ccmfBm is constructed:

$$X_t = \int_0^t L(t, s) dW_s.$$

(INVERSE) TRANSFER PRINCIPLE

THEOREM ((INVERSE) TRANSFER PRINCIPLE)

Let $f \in L^2$. Let X be the ccmfBm constructed from the Bm W .
Then

$$\int_0^T f(t) dX_t = \int_0^T L^* f(t) dW_t,$$
$$\int_0^T f(t) dW_t = \int_0^T (L^*)^{-1} f(t) dX_t,$$

where

$$L^* f(t) = af(t) + b \int_t^T f(s) \frac{\partial K_H}{\partial s}(s, t) ds,$$
$$(L^*)^{-1} f(t) = f(t)L^{-1}(T, t) + \int_t^T [f(s) - f(t)] L^{-1}(ds, t).$$

OUTLINE

- 1 CONSTRUCTION OF CCMFBM
- 2 MOTIVATION
- 3 (INVERSE) TRANSFER PRINCIPLE
- 4 APPLICATIONS**

APPLICATIONS

- Cameron–Martin–Girsanov–Hitsuda theorem, equivalence of laws
- Maximum likelihood estimation
- Prediction laws, bridges, conditional laws
- Simulation
- Malliavin calculus
- ...

Thank you for listening!
Any questions?